



# M SERIES BLUETOOTH ANALOG CORDED USER GUIDE

For M100B5, M100B10, M200B5, M200B10

# Table of Contents

M Series Bluetooth Analog Corded Phone Map .....	.3	Analog Guest Service Key Programming .....	.8
Unpacking Your Telephone .....	.4	Storing a Number into Memory Keys	
Installation .....	.4	or OneTouch Key .....	.8
Caution Information .....	.4	Programming Flash Timing and Pause Timing .....	.8
Connecting the Handset Cord .....	.4	Guest Card Samples .....	.9
Connecting the Line Cord .....	.4	Device Connection .....	.9
Operation .....	.4	Call Placement .....	.9
Placing a Call .....	.4	Play Bluetooth Audio .....	.9
Receiving a Call .....	.4	Important Safety Instructions .....	.11
Adjusting Ring Volume for Base .....	.5	FCC Interference Information .....	.12
Adjusting Speakerphone Volume .....	.5	FCC RF Radiation Exposure Statement .....	.12
Adjusting Handset Receiver Volume .....	.5	Industry of Canada Requirements .....	.12
Redial .....	.5	Requirements of Part 15—FCC Rules .....	.13
Using the HOLD Key .....	.5	Requirements of Part 68—FCC Rules .....	.13
Auto-Dial Keys—Faceplate O .....	.5	Technical Specifications .....	.15
Conference (2-line models only) .....	.5	User Guides .....	.15
Auto-Dial Keys—Faceplate On .....	.6	Service .....	.15
Programming .....	.6	Statement of Limited Warranty .....	.15
Bluetooth User Instructions .....	.7		
Bluetooth Use Cases .....	.8		

























the telephone company. The USOC Jack for this equipment is RJ11C.

A plug and jack used to connect this equipment to the premises wiring and telephone network must comply with the applicable FCC Part 68 rules and requirements adopted by ACTA. A compliant telephone cord and modular plug are provided with this telephone. It is designed to be connected to a compatible modular jack that is also compliant. See installation instructions for details.

The Ringer Equivalence Number (REN) is used to determine the number of devices that may be connected to a telephone line. Excessive RENs on a telephone line may result in the devices not ringing in response to an incoming call. In most but not all areas, the sum of RENs should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact the local telephone company. For products approved after July 23, 2001, the REN for this product is a part of the product identifier that has the format US:AAAEQ##TXXXX. The digits represented by ## are the REN without a decimal point (e.g., 03 is a REN of 0.3). For earlier products, the REN is separately shown on the label.

If this telephone causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. But if advance notice is not practical, the telephone company will notify the customer as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary.

The telephone company may make changes in its facilities, equipment, operations, or procedures that could affect the operation of the equipment. If this happens, the telephone company will provide advance notice in order for you to make the necessary modifications to maintain uninterrupted service.

If trouble is experienced with this equipment, for repair or warranty information, please contact Teledex at (800) 462-9446. If the equipment is causing harm to the telephone network, the telephone company may request that you disconnect the equipment until the problem is resolved.

There are no user-serviceable parts contained in this equipment.

Connection to party line service is subject to state tariffs. Contact the state public utility commission, public service commission, or corporation commission for information.

If your home has specially wired alarm equipment connected to the telephone line, ensure the installation of this product does not disable your alarm equipment. If you have questions about what will disable alarm equipment, consult your telephone company or a qualified installer.

This telephone is hearing aid compatible.

These telephone devices are intended for commercial use only, primarily in hotel guestrooms. They must be used with a PBX (private branch exchange), and are not intended to be connected directly to a PSTN line (public switched telephone network). There are no user-serviceable parts inside the equipment.



